



# MX280NI

## User Manual

Version 1.0

Published September 2013

Copyright©2013 BCM Advanced Research

All rights reserved.

---

Version 1.0  
Published September 2013  
Copyright©2013 BCM. All rights reserved.

### Copyright Notice:

No part of this documentation may be reproduced, transcribed, transmitted, or translated in any language, in any form or by any means, except duplication of documentation by the purchaser for backup purpose, without written consent of BCM.

Products and corporate names appearing in this documentation may or may not be registered trademarks or copyrights of their respective companies, and are used only for identification or explanation and to the owners' benefit, without intent to infringe.

### Disclaimer:

Specifications and information contained in this documentation are furnished for informational use only and subject to change without notice, and should not be constructed as a commitment by BCM. BCM assumes no responsibility for any errors or omissions that may appear in this documentation.

With respect to the contents of this documentation, BCM does not provide warranty of any kind, either expressed or implied, including but not limited to the implied warranties or conditions of merchantability or fitness for a particular purpose.

In no event shall BCM, its directors, officers, employees, or agents be liable for any indirect, special, incidental, or consequential damages (including damages for loss of profits, loss of business, loss of data, interruption of business and the like), even if BCM has been advised of the possibility of such damages arising from any defect or error in the documentation or product.

The terms HDMI™ and HDMI High-Definition Multimedia Interface, and the HDMI logo are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries.



This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

### CALIFORNIA, USA ONLY

The Lithium battery adopted on this motherboard contains Perchlorate, a toxic substance controlled in Perchlorate Best Management Practices (BMP) regulations passed by the California Legislature. When you discard the Lithium battery in California, USA, please follow the related regulations in advance.

“Perchlorate Material-special handling may apply, see [www.dtsc.ca.gov/hazardouswaste/perchlorate](http://www.dtsc.ca.gov/hazardouswaste/perchlorate)”

---

# Contents

<b>1</b>	<b>Introduction .....</b>	<b>4</b>
1.1	Package Contents .....	4
1.2	Specifications.....	5
1.3	Motherboard Layout.....	7
1.4	I/O Panel.....	9
<b>2</b>	<b>Installation .....</b>	<b>10</b>
2.1	Screw Holes.....	10
2.2	Pre-installation Precautions .....	10
2.3	Installation of Memory Modules (DIMM) .....	11
2.4	Expansion Slots .....	12
2.5	Jumpers Setup.....	13
2.6	Onboard Headers and Connectors.....	15
<b>3</b>	<b>UEFI SETUP UTILITY.....</b>	<b>20</b>
3.1	Introduction .....	20
3.1.1	UEFI Menu Bar .....	20
3.1.2	Navigation Keys .....	21
3.2	Main Screen.....	21
3.3	Advanced Screen.....	22
3.3.1	CPU Configuration .....	23
3.3.2	Super IO Configuration .....	24
3.3.3	Chipset Configuration.....	25
3.3.4	Storage Configuration .....	26
3.3.5	ACPI Configuration.....	27
3.3.6	USB Configuration .....	28
3.3.7	Voltage Configuration.....	29
3.4	Hardware Health Event Monitoring Screen .....	30
3.5	Boot Screen .....	31
3.6	Security Screen .....	32
3.7	Exit Screen .....	33

---

# Chapter 1: Introduction

Thank you for purchasing BCM **MX280NI** motherboard, a reliable motherboard produced under BCM's consistently stringent quality control. It delivers excellent performance with robust design conforming to BCM's commitment to quality and endurance.

In this manual, Chapter 1 and 2 contain introduction of the motherboard and step-by-step guide to the hardware installation. Chapter 3 and 4 contain the configuration guide to BIOS setup and information of the Support CD.



Because the motherboard specifications and the BIOS software might be updated, the content of this manual will be subject to change without notice. In case any modifications of this manual occur, the updated version will be available on BCM website without further notice.

If you require technical support related to this motherboard, please visit our website for specific information about the model you are using.

## 1.1 Package Contents

**MX280NI** Motherboard

(Mini-ITX Form Factor: 6.7-in x 6.7-in, 17.0 cm x 17.0 cm)

**MX280NI** Driver CD

**MX280NI** Jumper setting instruction


1 x I/O Panel Shield

## 1.2 Specifications

<b>Form Factor</b>	Dimensions	Mini-ITX (6.7-in x 6.7-in)
<b>Processor System</b>	CPU	- Intel® Dual-Core Atom™ CedarView Processor N2800 - Supports Hyper-Threading Technology
	Core Number	2
	Max Speed	1.86 GHz
	L3 Cache	N/A
	Chipset	NM10
	BIOS	UEFI
<b>Expansion Slot</b>	PCI	0
	Mini-PCIe	1 (Half Size) + 1 (Full Size, shared with m-SATA)
	mSATA	1 (share with mini-PCIe)
	PCIe	1 (x1)
	CFast Card Socket	0
<b>Memory</b>	Technology	Single Channel DDR3 800/1066 MHz SDRAM
	Max.	4GB
	Socket	2 x SODIMM
<b>Graphics</b>	Controller	Intel® GMA3650
	VRAM	Shared Memory
	VGA	Supports max. resolution 1920 x 1200
	LVDS	Dual channel 24-bit, max resolution 1920 x 1200@60Hz
	HDMI	1
	DVI	No
	DisplayPort	No
	Multi Display	Yes (Dual Display)
<b>Ethernet</b>	Ethernet	10/100/1000 Mbps
	Controller	GbE LAN: 1 x Intel® 82574L
	Connector	1 x RJ-45
<b>SATA</b>	Max Data Transfer Rate	SATA2 (3.0Gb/s)
<b>Rear I/O</b>	VGA	1
	DVI	0
	HDMI	1

	DisplayPort	0
	Ethernet	1
	USB	4
	Audio	2 (Mic-In, Line-Out)
	Serial	0
	PS/2	0
<b>Internal Connector</b>	USB	4 (USB 2.0 compliant)
	LVDS/ Inverter	1/1
	VGA	1 (shared with rear I/O VGA COM)
	Serial	2 ( RS232) / 4 from TPM header
	SATA	2 x SATA2 ( 3.0Gb/s)
	mPCIe	1 + 1 shared
	Parallel	1
	mSATA	1 shared
	IrDA	0
	GPIO 8-bit	4 in / 4 out
	SATA PWR Output Con	1
	Speaker Header	1
<b>Watchdog Timer</b>	Output	From Super I/O to RESET signal
	Interval	256 Segments, 0,1,2...255 Sec/Min
<b>Power Requirements</b>	Input PWR	9~19V DC-In (DC-Jack or 2-pin PWR Con)
	Power On	AT/ATX Supported -AT : Directly PWR on as power input ready -ATX : Press button to PWR on after power input ready
<b>Environment</b>	Temperature	0°C – 60°C


## 1.3 Motherboard Layout



- 
- 1 : INT\_DC1 Power Input/Output
  - 2 : UPS\_IN1 UPS power input
  - 3 : DC\_CTL1 Input power select
  - 4 : SATA\_PWR1 SATA Power output connector
  - 5 : AMP\_CTL1 Audio amp control
  - 6 : BLT\_PWM1 Backlight PWM voltage select
  - 7 : LVDS1 LVDS output
  - 8 : BLT\_CTL1 Backlight output
  - 9 : PNL\_PWR1 LVDS voltage select
  - 10 : BKT\_PWR1 Backlight voltage select
  - 11 : JGPIO\_PWR1 GPIO Pin-9 power select
  - 12 : JGPIO1 GPIO header
  - 13 : CPU\_FAN1 CPU fan
  - 14 : PWR\_JP1 ATX/AT mode select
  - 15 : Panel1 Front Panel header
  - 16 : USB4\_5 USB2.0 header
  - 17 : USB6\_7 USB2.0 header
  - 18 : DMIC1 Digital microphone header
  - 19 : COM1 RS-232 Port 4 Pin Header
  - 20 : COM2 RS-232 Port 4 Pin Header
  - 21 : PS2\_KB\_MS1 PS2 Keyboard/Mouse header
  - 22 : LPT1 Printer port header
  - 23 : TPM1 TPM header
  - 24 : CS1 Custom Solutions header
  - 25 : SPDIF1 S/PDIF header
  - 26 : HD\_AUDIO1 Front Panel Audio header
  - 27 : SPEAKER1 3W Amplified Audio header
  - 28 : CHA\_FAN1 Chassis fan
  - 29 : CI1, CI2 Chassis Intrusion header
  - 30 : CLRCMOS1 Clear CMOS header
  - 31 : MSATA\_SEL1 mSATA select
  - 32 : VGA2 VGA header
  - 33 : SATAII\_1, SATAII\_2 SATA2 connector
-



## 1.4 I/O Panel




- |     |                        |   |                        |
|-----|------------------------|---|------------------------|
| 1   | DC Jack (DC_JACK1)     | 5 | USB 2.0 Ports (USB2_3) |
| 2   | USB 2.0 Ports (USB0_1) | 6 | HDMI Port (HDMI1)      |
| * 3 | LAN RJ-45 Port (LAN1)  | 7 | Line out (Lime)        |
| 4   | VGA Port (VGA1)        | 8 | Microphone (Pink)      |

\* There are two LED next to the LAN port. Please refer to the table below for the LAN port LED indications.

### LAN Port LED Indications

Activity/Link LED	
Status	Description
Off	No Link
Blinking	Data Activity
On	Link

SPEED LED	
Status	Description
Off	10Mbps connection
Orange	100Mbps connection
Green	1Gbps connection



---

## Chapter 2: Installation

This is a Mini-ITX form factor (6.7" x 6.7", 17.0 x 17.0 cm) motherboard. Before you install the motherboard, study the configuration of your chassis to ensure that the motherboard fits into it.



Make sure to unplug the power cord before installing or removing the motherboard. Failure to do so may induce physical injuries to you and/or cause damage to motherboard components.

### 2.1 Screw Holes

Place screws into the holes to secure the motherboard to the chassis.



Do not over-tighten the screws! Doing so may damage the motherboard.

### 2.2 Pre-installation Precautions

Take note of the following precautions before you install motherboard components or change any motherboard settings.

1. Unplug the power cord from the wall socket before touching any component.
2. To avoid damaging the motherboard components due to static electricity, NEVER place your motherboard directly on the carpet or the like. Also remember to use a grounded wrist strap or touch a safety grounded object before you handle components.
3. Hold components by the edges and do not touch the ICs.
4. Whenever you uninstall any component, place it on a grounded antistatic pad or in the bag that comes with the component.




Before you install or remove any component, ensure that the power is switched off or the power cord is detached from the power supply. Failure to do so may cause severe damage to the motherboard, peripherals, and/or components.

---

## 2.3 Installation of Memory Modules (SO-DIMM)

This motherboard provides two 204-pin DDR3 (Double Data Rate 3) SO-DIMM slots.

- Step 1. Align a DIMM on the slot such that the notch on the DIMM matches the break on the slot.



The DIMM only fits in one correct orientation. It will cause permanent damage to the motherboard and the DIMM if you force the DIMM into the slot at incorrect orientation.

- Step 2. Firmly insert the DIMM into the slot until the retaining clips at both ends fully snap back in place and the DIMM is properly seated.

---

## 2.4 Expansion Slots (PCI Express, mini-PCle and mini-PCle/mini-SATA Slots)

There is 1 PCI Express slot, 1 mini-PCle slot and 1 mini-PCle/mini-SATA slot on this motherboard.

**PCIE slot:** PCIE1 (PCIE x1 slot) is used for PCI Express x1 lane width graphics cards.

**mini-PCle slot:**

MINI\_PCIE2 (mini-PCle slot; half size) is used for PCI Express mini cards.

**mini-PCle/mini-SATA slot:**


MINI\_PCIE1 (mini-PCle/mini-SATA slot; full size) is used for PCI Express mini cards or mSATA cards.



### Installing an expansion card

- Step 1. Before installing the expansion card, please make sure that the power supply is switched off or the power cord is unplugged. Please read the documentation of the expansion card and make necessary hardware settings for the card before you start the installation.
- Step 2. Remove the system unit cover (if your motherboard is already installed in a chassis).
- Step 3. Remove the bracket facing the slot that you intend to use. Keep the screws for later use.
- Step 4. Align the card connector with the slot and press firmly until the card is completely seated on the slot.
- Step 5. Fasten the card to the chassis with screws.
- Step 6. Replace the system cover.

## 2.5 Jumpers Setup


The illustration shows how jumpers are setup. When the jumper cap is placed on pins, the jumper is “Short”. If no jumper cap is placed on pins, the jumper is “Open”. The illustration shows a 3-pin jumper whose pin1 and pin2 are “Short” when jumper cap is placed on these 2 pins.



Jumper	Setting	Description
Clear CMOS Jumper (3-pin CLRCMOS1) (see p.7, No. 30)	 <b>1_2</b> Default	 <b>2_3</b> Clear CMOS

Note: CLRCMOS1 allows you to clear the data in CMOS. To clear and reset the system parameters to default setup, please turn off the computer and unplug the power cord from the power supply. After waiting for 15 seconds, use a jumper cap to short pin2 and pin3 on CLRCMOS1 for 5 seconds. However, please do not clear the CMOS right after you update the BIOS. If you need to clear the CMOS when you just finish updating the BIOS, you must boot up the system first, and then shut it down before you do the clear-CMOS action. Please be noted that the password, date, and time will be cleared only if the CMOS battery is removed.

AMP\_CTL1  
(3-pin AMP\_CTL1)  
(see p.7, No. 5)



1 2 3


PIN	Signal Name
1	GPIO_VOL_UP
2	GND
3	GPIO_VOL_DW

BLT_PWM1 (3-pin BLT_PWM1) (see p.7, No. 6)		1-2 : +3V 2-3 : +5V
--	---	------------------------

BLT\_CTL1

(8-pin BLT\_CTL1)

(see p.7, No. 8)



PIN	Signal Name
1	CON_LBKLT_EN
2	CON_LBKLT_CTL
3	LCD_BLT_VCC
4	LCD_BLT_VCC
5	GND
6	GND
7	GPIO_BLT_UP
8	GPIO_BLT_DW

---

DC\_CLT1  
(2-pin DC\_CTL1)  
(see p.7, No. 3)



Power Input Voltage > +12V: Short  
Power Input Voltage ≤ +12V: Open

---

Panel Power Selection  
(4-pin PNL\_PWR1)  
(see p.7, No. 9)



3-1: +3.3V LVDS Voltage  
3-4: +12V LVDS Voltage  
3-5: +5V LVDS Voltage

---


Backlight Power Selection  
(4-pin BKT\_PWR1)  
(see p.7, No. 10)



3-1: +5V Backlight Voltage  
3-4: +Vin Backlight Voltage  
3-5: +12V Backlight Voltage

---


Digital Input / Output Power Select  
(3-pin JGPIO\_PWR1)  
(see p.7, No. 11)



1-2 : +12V  
2-3 : +5V

---


ATX/AT Mode Selection  
(3-pin PWR\_JP1)  
(see p.7, No. 14)



1-2 : AT Mode  
2-3 : ATX Mode

---

MSATA\_SEL1 (Disable SATAII\_2)  
(3-pin MSATA\_SEL1)  
(see p.7, No. 31)



1-2 : mPCIe  
2-3 : mSATA (Disable SATAII\_2)


# 2.6 Onboard Headers and Connectors



Onboard headers and connectors are NOT jumpers. Do NOT place jumper caps over these headers and connectors. Placing jumper caps over the headers and connectors will cause permanent damage of the motherboard!

## LVDS Panel Connector


(40-pin LVDS1)  
(see p.7, No. 7)



PIN	Signal Name	PIN	Signal Name
2	+LVDD	1	+LVDD
4	NC	3	+3V
6	LVDS_A_DATA0#	5	NC
8	GND	7	LVDS_A_DATA0
10	LVDS_A_DATA1	9	LVDS_A_DATA1#
12	LVDS_A_DATA2#	11	GND
14	GND	13	LVDS_A_DATA2
16	LVDS_A_DATA3	15	LVDS_A_DATA3#
18	LVDS_A_CLK#	17	GND
20	GND	19	LVDS_A_CLK
22	LVDS_B_DATA0	21	LVDS_B_DATA0#
24	LVDS_B_DATA1#	23	GND
26	GND	25	LVDS_B_DATA1
28	LVDS_B_DATA2	27	LVDS_B_DATA2#
30	LVDS_B_DATA3#	29	DPLVDD_EN
32	GND	31	LVDS_B_DATA3
34	LVDS_B_CLK	33	LVDS_B_CLK#
36	CON_LBKLT_EN_R	35	GND
38	LCD_BLT_VCC	37	CON_LBKLT_CTL_R
40	LCD_BLT_VCC	39	LCD_BLT_VCC

## Digital Input / Output Pin Header

(10-pin JGPIO1)  
(see p.7, No. 12)



PIN	Signal Name	PIN	Signal Name
1	Digital Output 0	2	Digital Input 0
3	Digital Output 1	4	Digital Input 1
5	Digital Output 2	6	Digital Input 2
7	Digital Output 3	8	Digital Input 3
9	JGPIOPWR	10	GND

## UPS Module Power Input Connector

(2-pin DC\_UPS1)  
(see p.7, No. 2)



## ATX Power Input/Output Connector


(2-pin INT\_DC1)  
(see p.7, No. 1)




(see p.7, No. 4)



(9-pin COM2: see p.7, No. 20)



(see p.7 No. 13)




Please connect the CPU fan cable to the connector and match the black wire to the ground pin.




Though this motherboard provides 4-Pin CPU fan (Quiet Fan) support, the 3-Pin CPU fan still can work successfully even without the fan speed control function. If you plan to connect the 3-Pin CPU fan to the CPU fan connector on this motherboard, please connect it to Pin 1-3.

Pin 1-3 Connected 

### 3-Pin Fan Installation




(see p.7, No. 28)



Please connect the fan cable to the fan connector and match the black wire to the ground pin.

(3-pin SPDIF1: see p.7, No. 25)



(10-pin VGA2: see p.7, No. 32)




PIN	Signal Name	PIN	Signal Name
1	RED	2	GND
3	GRN	4	GND
5	BLUE	6	GND
7	HSYNC	8	VSYNC
9	DDC_CLK	10	DDC_DATA



System Panel Header

(9-pin PANEL1)  
(see p.7, No. 15)



This header accommodates several system front panel functions.



Connect the power switch, reset switch and system status indicator on the chassis to this header according to the pin assignments below. Note the positive and negative pins before connecting the cables.

**PWRBTN (Power Switch):**

Connect to the power switch on the chassis front panel. You may configure the way to turn off your system using the power switch.

**RESET (Reset Switch):**

Connect to the reset switch on the chassis front panel. Press the reset switch to restart the computer if the computer freezes and fails to perform a normal restart.

**PLED (System Power LED):**

Connect to the power status indicator on the chassis front panel. The LED is on when the system is operating. The LED keeps blinking when the system is in S1/S3 sleep state. The LED is off when the system is in S4 sleep state or powered off (S5).

**HDLED (Hard Drive Activity LED):**

Connect to the hard drive activity LED on the chassis front panel. The LED is on when the hard drive is reading or writing data.

The front panel design may differ by chassis. A front panel module mainly consists of power switch, reset switch, power LED, hard drive activity LED, speaker and etc. When connecting your chassis front panel module to this header, make sure the wire assignments and the pin assignments are matched correctly.

SATA2 Connectors

(SATAII\_1/SATAII\_2:  
see p.8, No. 33)



These two Serial ATA2 (SATA2) connectors support SATA data cables for internal storage devices. The current SATA2 interface allows up to 3.0 Gb/s data transfer rate.

3W Audio Amp Output Wafer


(4-pin SPEAKER1)  
(see p.7, No. 27)



PIN	Signal Name
1	SPK L-
2	SPK L+
3	SPK R+
4	SPK R-

USB 2.0 Headers

(9-pin USB4\_5: see p.7, No. 16)  
(9-pin USB6\_7: see p.7, No. 17)



Besides four default USB 2.0 ports on the I/O panel, there are two USB 2.0 headers on this motherboard. Each USB 2.0 header can support two USB 2.0 ports.

Chassis Intrusion Headers


(2-pin CI1/CI2: see p.7, No. 29)



This motherboard supports CASE OPEN detection feature that detects if the chassis cover has been removed. This feature requires a chassis with chassis intrusion detection design.

Front Panel Audio Header


(9-pin HD\_AUDIO1)  
(see p.7 No. 26)



This is an interface for front panel audio cable that allows convenient connection and control of audio devices.

TPM Header


(17-pin TPM1)  
(see p.7, No. 23)



This connector supports a Trusted Platform Module (TPM) system, which can securely store keys, digital certificates, passwords, and data. A TPM system also helps enhance network security, protects digital identities, and ensures platform integrity.

PS2\_KB\_MS1


(8-pin PS2\_KB\_MS1)  
(see p.7, No. 21)



PIN	Signal Name
1	KBCLK
2	+5V
3	KBDATA
4	+5V
5	MSDATA
6	GND
7	MSCLK
8	GND

Print Port Header

(25-pin LPT1)  
(see p.7, No. 22)



This is an interface for print port cable that allows convenient connection of printer devices.

DMIC1

(4-pin DMIC1)  
(see p.7, No. 18)



PIN	Signal Name
1	+3V
2	DMIC_DATA
3	GND
4	DMIC_CLK
5	NC

CS1

(9-pin CS1)  
(see p.7, No. 24)



PIN	Signal Name
1	Watch Dog Timer
2	Ground
3	NC
4	SMB_CLK_RESUME
5	+3.3V standby
6	SMB_DATA_RESUME
7	PWRBT#
8	CIRRX
9	+5.0V standby
10	Ground

---

## Chapter 3: UEFI SETUP UTILITY

### 3.1 Introduction

This section explains how to use the UEFI SETUP UTILITY to configure your system. The UEFI chip on the motherboard stores the UEFI SETUP UTILITY. You may run the UEFI SETUP UTILITY when you start up the computer. Please press <F2> or <Del> during the Power-On-Self-Test (POST) to enter the UEFI SETUP UTILITY, otherwise, POST will continue with its test routines.

If you wish to enter the UEFI SETUP UTILITY after POST, restart the system by pressing <Ctl> + <Alt> + <Delete>, or by pressing the reset button on the system chassis. You may also restart by turning the system off and then back on.



Because the UEFI software is constantly being updated, the following UEFI setup screens and descriptions are for reference purpose only, and they may not exactly match what you see on your screen.

#### 3.1.1 UEFI Menu Bar

The top of the screen has a menu bar with the following selections:

<b>Main</b>	To set up the system time/date information
<b>Advanced</b>	To set up the advanced UEFI features
<b>H/W Monitor</b>	To display current hardware status
<b>Boot</b>	To set up the default system device to locate and load the Operating System
<b>Security</b>	To set up the security features
<b>Exit</b>	To exit the current screen or the UEFI SETUP UTILITY

Use <←> key or <→> key to choose among the selections on the menu bar, and then press <Enter> to get into the sub screen. You can also use the mouse to click your required item.

## 3.1.2 Navigation Keys

Please check the following table for the function description of each navigation key.

Navigation Key(s)	Function Description
← / →	Moves cursor left or right to select Screens
↑ / ↓	Moves cursor up or down to select items
+ / -	To change option for the selected items
<Enter>	To bring up the selected screen
<F1>	To display the General Help Screen
<F7>	Discard changes
<F9>	To load optimal default values for all the settings
<F10>	To save changes and exit the UEFI SETUP UTILITY
<F12>	Print screen
<ESC>	To jump to the Exit Screen or exit the current screen

## 3.2 Main Screen


When you enter the UEFI SETUP UTILITY, the Main screen will appear and display the system overview.



---

### 3.3 Advanced Screen

In this section, you may set the configurations for the following items: CPU Configuration, Super IO Configuration, Chipset Configuration, Storage Configuration, ACPI Configuration, USB Configuration and Voltage Configuration.




Setting wrong values in this section may cause the system to malfunction.

#### Instant Flash

Instant Flash is a UEFI flash utility embedded in Flash ROM. This convenient UEFI update tool allows you to update system UEFI without entering operating systems first like MS-DOS or Windows®. Just launch this tool and save the new UEFI file to your USB flash drive, floppy disk or hard drive, then you can update your UEFI only in a few clicks without preparing an additional floppy diskette or other complicated flash utility. Please be noted that the USB flash drive or hard drive must use FAT32/16/12 file system. If you execute Instant Flash utility, the utility will show the UEFI files and their respective information. Select the proper UEFI file to update your UEFI, and reboot your system after UEFI update process completes.

---

### 3.3.1 CPU Configuration




#### Intel Hyper Threading Technology

To enable this feature, it requires a computer system with an Intel processor that supports Hyper-Threading technology and an operating system that includes optimization for this technology, such as Microsoft® Windows® 8 / 7. Set to [Enabled] if using Microsoft® Windows® 8 / 7.

#### No-Excute Memory Protection

No-Execution (NX) Memory Protection Technology is an enhancement to the IA-32 Intel Architecture. An IA-32 processor with “No Execute (NX) Memory Protection” can prevent data pages from being used by malicious software to execute code.

### 3.3.2 Super IO Configuration



#### COM1 Configuration

Use this to set parameters of COM1.

#### COM2 Configuration

Use this to set parameters of COM2.

#### LPT1 Port Configuration

Use this set parameters of the onboard parallel port.


#### WDT Timeout Reset

This allows users to enable/disable the Watch Dog Timer timeout to reset system. The default value is [Disabled].



---

### 3.3.3 Chipset Configuration



#### Panel Type Selection

Use this to select panel type. The default value is [1366x768/18-bit/1-ch/LED].

#### Primary Graphics Adapter

This allows you to select the boot graphic adapter priority. The default value is [VBIOS Default].

#### ACPI HPET Table

Use this item to enable or disable ACPI HPET Table. The default value is [Enabled]. Please set this option to [Enabled] if you plan to use this motherboard to submit Windows® certification.

#### Restore on AC/Power Loss

This allows you to set the power state after an unexpected AC/power loss. If [Power Off] is selected, the AC/power remains off when the power recovers. If [Power On] is selected, the AC/power resumes and the system starts to boot up when the power recovers.

#### Onboard HD Audio

Select [Auto], [Enabled] or [Disabled] for the onboard HD Audio feature. If you select [Auto], the onboard HD Audio will be disabled when PCI Sound Card is plugged.

##### Front Panel

Select [Auto] or [Disabled] for the onboard HD Audio Front Panel.

#### Onboard LAN1

This allows you to enable or disable the “Onboard LAN1” feature.

### 3.3.4 Storage Configuration



#### SATA Mode

Use this to select SATA mode. Configuration options: [IDE Mode], [AHCI Mode] and [Disabled]. The default value is [IDE Mode].




AHCI (Advanced Host Controller Interface) supports NCQ and other new features that will improve SATA disk performance but IDE mode does not have these advantages.

#### Hard Disk S.M.A.R.T.

Use this item to enable or disable the S.M.A.R.T. (Self-Monitoring, Analysis, and Reporting Technology) feature. Configuration options: [Disabled] and [Enabled].

---

### 3.3.5 ACPI Configuration



#### **Suspend to RAM**

Use this item to select whether to auto-detect or disable the Suspend-to-RAM feature. Select [Auto] will enable this feature if the OS supports it.

#### **S3 Video Repost**

Use this to enable/disable S3 Video Repost. The default value is [Enabled].

#### **Check Ready Bit**

Use this item to enable or disable the feature Check Ready Bit.

#### **Deep S5**

Use this item to enable or disable Deep S5. The default value is [Auto].

#### **PS/2 Keyboard Power On**

Use this item to enable or disable PS/2 keyboard to turn on the system from the power-soft-off mode.

#### **PCI Devices Power On**

Use this item to enable or disable PCI devices to turn on the system from the power-soft-off mode.

#### **RTC Alarm Power On**

Use this item to enable or disable RTC (Real Time Clock) to power on the system.


#### **USB Keyboard/Remote Power On**

Use this item to enable or disable USB Keyboard/Remote to power on the system.

#### **USB Mouse Power On**

Use this item to enable or disable USB Mouse to power on the system.

### 3.3.6 USB Configuration



#### USB 2.0 Controller

Use this item to enable or disable the use of USB 2.0 controller.

#### Legacy USB Support

Use this option to select legacy support for USB devices. There are four configuration options: [Enabled], [Auto], [Disabled] and [UEFI Setup Only]. The default value is [Enabled]. Please refer to below descriptions for the details of these four options:

[Enabled] - Enables support for legacy USB.


[Auto] - Enables legacy support if USB devices are connected.

[Disabled] - USB devices are not allowed to use under legacy OS and UEFI setup when [Disabled] is selected. If you have USB compatibility issue, it is recommended to select [Disabled] to enter OS.

[UEFI Setup Only] - USB devices are allowed to use only under UEFI setup and Windows / Linux OS.

---

### 3.3.7 Voltage Configuration




#### DRAM Voltage

Use this to select DRAM Voltage. The default value is [1.55V].

---

### 3.4 Hardware Health Event Monitoring Screen

In this section, it allows you to monitor the status of the hardware on your system, including the parameters of the CPU temperature, motherboard temperature, CPU fan speed, chassis fan speed, and the critical voltage.



#### CPU\_FAN1 Setting

This allows you to set CPU\_FAN1's speed. Configuration options: [Full On] and [Automatic Mode]. The default value is [Full On].

#### CHA\_FAN1 Setting

This allows you to set CHA\_FAN1's speed. Configuration options: [Full On] and [Automatic Mode]. The default value is [Full On].

#### Case Open Feature

This allows you to enable or disable case open detection feature. The default is value [Disabled].

#### Clear Status

This option appears only when the case open has been detected. Use this option to keep or clear the record of previous chassis intrusion status.

In this section, it will display the available devices on your system for you to configure the boot settings and the boot priority.



This shows the number of seconds to wait for setup activation key.  
65535(0xFFFF) means indefinite waiting.

If this item is set to [On], it will automatically activate the Numeric Lock function after boot-up.


Use this item to enable or disable OEM Logo. The default value is [Enabled].

Use this item to enable or disable the Boot From Onboard LAN feature.

---

### 3.6 Security Screen


In this section, you may set, change or clear the supervisor/user password for the system.





---

## 3.7 Exit Screen



### Save Changes and Exit

When you select this option, it will pop-out the following message, “Save configuration changes and exit setup?” Select [OK] to save the changes and exit the UEFI SETUP UTILITY.

### Discard Changes and Exit

When you select this option, it will pop-out the following message, “Discard changes and exit setup?” Select [OK] to exit the UEFI SETUP UTILITY without saving any changes.

### Discard Changes

When you select this option, it will pop-out the following message, “Discard changes?” Select [OK] to discard all changes.

### Load UEFI Defaults

Load UEFI default values for all the setup questions. F9 key can be used for this operation.

### Launch EFI Shell from filesystem device

Attempts to Launch EFI Shell application (Shell64.efi) from one of the available filesystem devices.