

Quick Installation Guide

IGPS-9622DGP+-BT










Industrial Managed PoE Gigabit Switch

Introduction

IGPS-9622DGP+-BT is Layer-2 managed Gigabit Ethernet switch with 6x10/100/1000Base-T(X) P.S.E ports and 2x 100/1G/2.5G Base-T(X) P.S.E ports + 2x 1G/10GBase-X SFP ports. The switch support Ethernet Redundancy protocol, **O-Ring** (recovery time < 30ms) and MSTP (RSTP/STP compatible) can protect your mission-critical applications from network interruptions or temporary malfunctions with its fast recovery technology. **IGPS-9622DGP+-BT** also support Power over Ethernet, a system to transmit electrical power up to 90 watts, along with data, to remote devices over standard twisted-pair cable in an Ethernet network. Each **IGPS-9622DGP+-BT** switch has 6x10/100/1000Base-T(X) and 2x100/1G/2.5G Base-T(X) P.S.E. (Power Sourcing Equipment) ports. P.S.E. is a device (switch or hub for instance) that will provide power in a PoE connection. And support wide operating temperature from -40°C to 75°C. **IGPS-9622DGP+-BT** can also be managed centralized and convenient by Open-Vision, Except the Web-based interface, Telnet and console (CLI) configuration. Therefore, the switch is one of the most reliable choice for highly-managed and Fiber Ethernet application.

Package Contents

The device is shipped with the following items. If any of these items is missing or damaged, please contact your customer service representative for assistance.

Contents	Pictures	Number	Contents	Pictures	Number
IGPS-9622DGP+-BT		X 1	SFP Dust cover		X 2
CD		X 1	RJ 45 Dust cover		X 8
DIN-rail Kit		X 1	Wall-mounting Kit		X 2
Console Cable		X 1			
QIG		X 1			
6-pin terminal block		X 1			

Preparation

Before you begin installing the switch, make sure you have all of the package contents available and a PC with Microsoft Internet Explorer 6.0 or later, for using web-based system management tools.


Safety & Warnings

Elevated Operating Ambient: If installed in a closed or multi-unit rack assembly, the operating ambient temperature of the rack environment may be greater than room ambient. Therefore, consideration should be given to installing the equipment in an environment compatible with the maximum ambient temperature (T_{ma}) specified by the manufacturer.


Reduced Air Flow: Installation of the equipment in a rack should be such that the amount of air flow required for safe operation of the equipment is not compromised.

- Mechanical Loading:** Mounting of the equipment in the rack should be such that a hazardous condition is not achieved due to uneven mechanical loading.
- Circuit Overloading:** Consideration should be given to the connection of the equipment to the supply circuit and the effect that overloading of the circuits might have on overcurrent protection and supply wiring. Appropriate consideration of equipment nameplate ratings should be used when addressing this concern.

Dimension




Panel Layouts



Installation


DIN-rail Installation

- Step 1:** Slant the switch and screw the Din-rail kit onto the back of the switch, right in the middle of the back panel.
- Step 2:** Slide the switch onto a DIN-rail from the Din-rail kit and make sure the switch clicks into the rail firmly.



Wall-mounting

- Step 1:** Screw the two pieces of wall-mount kits onto both ends of the rear panel of the switch. A total of six screws are required, as shown below.
- Step 2:** Use the switch, with wall mount plates attached, as a guide to mark the correct locations of the four screws.
- Step 3:** Insert screws through the round screw holes (as shown below on the left) on the slides or through the cross-shaped aperture (as shown below on the right) in the middle of the plate and fasten the screw to the wall with a screwdriver.
- Step 4:** If the screw goes through the cross-shaped aperture, slide the switch down before tightening the screw.



Network Connection

The switch provides standard Ethernet ports. According to the link type, the switch uses CAT 3, 4, 5, 5e UTP cables to connect to any other network devices (PCs, servers, switches, routers, or hubs). Please refer to the following table for cable specifications.

Cable Types and Specifications:

Speed	Cable Type	Max. Length	Connector
10BASE-T	Cat. 3, 4, 5 100-ohm	UTP 100 m (328 ft)	RJ-45
100BASE-TX	Cat. 5 100-ohm UTP	UTP 100 m (328 ft)	RJ-45
1000BASE-T	Cat. 5 / Cat. 5e 100-ohm UTP or above	UTP 100 m (328 ft)	RJ-45
2.5GBASE-T	Cat. 5 / Cat. 5e 100-ohm UTP or above	UTP 100 m (328 ft)	RJ-45

Quick Installation Guide

IGPS-9622DGP+-BT

Industrial Managed PoE Gigabit Switch

Specifications

ORing Switch Model	IGPS-9622DGP+-BT
Physical Ports	
10/100/1000Base-T(X) with P.S.E. Ports in RJ45 Auto MDI/MDIX	6
100/1G/2.5GBase-T(X) with P.S.E. Ports in RJ45 Auto MDI/MDIX	2
1G/10GBase-X with SFP port	2
Technology	
Ethernet Standards	IEEE 802.3 for 10Base-T IEEE 802.3u for 100Base-TX and 100Base-FX IEEE 802.3ab for 1000Base-T IEEE 802.3z for 1000Base-X IEEE 802.3bz for 2.5GBase-T IEEE 802.3ae for 10Gigabit Ethernet IEEE 802.3x for Flow control IEEE 802.3ad for LACP (Link Aggregation Control Protocol) IEEE 802.1p for COS (Class of Service) IEEE 802.1Q for VLAN Tagging IEEE 802.1d for STP (Spanning Tree Protocol) IEEE 802.1w for RSTP (Rapid Spanning Tree Protocol) IEEE 802.1s for MSTP (Multiple Spanning Tree Protocol) IEEE 802.1x for Authentication IEEE 802.1AB for LLDP (Link Layer Discovery Protocol) IEEE 802.3af/at/bt PoE specification (Per port up to 90 watts PoE output)
MAC Table	16K
Priority Queues	8
Processing	Store-and-Forward
Packet Buffer	8Mbits
Switch Properties	Switching latency: 7 us Switching bandwidth: 62Gbps Throughput (packet per second) : 46.13Mpps@64Bytes packet Max. Number of Available VLANs: 4096 (ID Range : VID 0 to 4095) IGMP multicast groups: 64 for each VLAN Port rate limiting: User Define
Jumbo frame	Up to 10K Bytes
Security Features	Device Binding security feature Enable/disable ports, MAC based port security VLAN (802.1Q) to segregate and secure network traffic RADIUS/TACACS+ centralized password management SNMPv3 encrypted authentication and access security HTTPS / SSH / SSL enhance network security DOS/DDOS auto prevention IP Source Guard
Software Features	Redundant Ring (O-Ring) with recovery time less than 30ms Quality of Service (802.1p) for real-time traffic VLAN (802.1Q) with VLAN tagging IGMP Snooping IP-based bandwidth management Application-based QoS management Port configuration, status, statistics, monitoring, security DHCP Server/Client/Relay SMTP Client Modbus TCP NTP server/client
QoS	TOS/Diffserv supported Cos Application based QoS IP based bandwidth management
Network Redundancy	O-Ring, O-chain, MRP, NOTE , STP/RSTP/MSTP (IEEE 802.1d/w/s)
PoE Management	PoE configuration PoE Status PoE Scheduling (turn on/off the PoE device) Auto-Ping check (Reboot PDs if there is no responses)
RS-232 Serial Console Port	RS-232 in RJ45 connector with console cable. Baud rate setting: 115200bps, 8, N, 1
Fault contact	
Relay	Relay output to carry capacity of 1A at 24VDC
Reset Function	
Reset Button	< 5 sec: System reboot, > 5 sec: Factory default
Power	
Redundant Input power	Dual DC inputs. 50~57VDC on 6-pin terminal block: IEEE 802.3af PoE output @ 50~57VDC input, IEEE 802.3at PoE output @ 52~57VDC input, IEEE 802.3bt (Type 4) PoE output @ 55~57VDC input
Power consumption(Typ.)	23.8 Watts (without any PoE power output)
Total PoE power budget	240W max, per port up to max. 90W
Overload current protection	Present
Reverse polarity protection	Not present, switch isn't working without any damage
Physical Characteristic	
Enclosure	IP-30
Dimension (W x D x H)	65 (W) x 160.2(D) x 153.6(H) mm (2.55 x 6.30 x 6.04 inch)
Weight (g)	1400g
Environmental	
Storage Temperature	-40 to 85°C (-40 to 185°F)
Operating Temperature	-40 to 75°C (-40 to 167°F)
Operating Humidity	5% to 95% Non-condensing
Regulatory Approvals	
EMC	CE EMC (EN 55024, EN 55032), FCC Part 15 B
EMI	EN 55032, CISPR32, EN 61000-3-2, EN 61000-3-3, FCC Part 15 B class A
EMS	IEC/EN 61000-4-2 (ESD), IEC/EN 61000-4-3 (RS), IEC/EN 61000-4-4 (EFT), IEC/EN 61000-4-5 (Surge), IEC/EN 61000-4-6 (CS) IEC/EN 61000-4-8 (PFMF)
Shock	IEC60068-2-27
Free Fall	IEC60068-2-31
Vibration	IEC60068-2-6
Warranty	5 years

*Note : This function is available by request only

For pin assignments for different types of cables, please refer to the following tables.

10/100Base-T(X) P.S.E. RJ-45 port		
Pin No.	Description	
#1	TD+ with PoE Power Output -	
#2	TD- with PoE Power Output -	
#3	RD+ with PoE Power Output +	
#4	Not used	
#5	Not used	
#6	RD- with PoE Power Output +	
#7	Not used	
#8	Not used	

1G/2.5GBase-T P.S.E. RJ-45 port		
Pin No.	Description	
#1	BI_DA+ with PoE Power Output -	
#2	BI_DA- with PoE Power Output -	
#3	BI_DB+ with PoE Power Output +	
#4	BI_DC+ with PoE Power Output +	
#5	BI_DC- with PoE Power Output +	
#6	BI_DB- with PoE Power Output +	
#7	BI_DD+ with PoE Power Output -	
#8	BI_DD- with PoE Power Output -	

1000 Base-T(X) RJ-45 Port		
Pin Number	Assignments	
1	BI_DA+	
2	BI_DA-	
3	BI_DB+	
4	BI_DC+	
5	BI_DC-	
6	BI_DB-	
7	BI_DD+	
8	BI_DD-	

10/100 Base-T(X) RJ-45 Port		
Pin Number	Assignments	
1	TD+	
2	TD-	
3	RD-	
4	Not used	
5	Not used	
6	RD-	
7	Not used	
8	Not used	

10/100Base-T RJ-45 Port			
Pin Number	MDI port	MDI-X port	
1	TD+(transmit)	RD+(receive)	
2	TD-(transmit)	RD-(receive)	
3	RD+(receive)	TD+(transmit)	
4	Not used	Not used	
5	Not used	Not used	
6	RD-(receive)	TD-(transmit)	
7	Not used	Not used	
8	Not used	Not used	

1000Base-T MDI/MDI-X			
Pin Number	MDI port	MDI-X port	
1	BI_DA+	BI_DB+	
2	BI_DA-	BI_DB-	
3	BI_DB+	BI_DA+	
4	BI_DC+	BI_DD+	
5	BI_DC-	BI_DD-	
6	BI_DB-	BI_DA-	
7	BI_DD+	BI_DC+	
8	BI_DD-	BI_DC-	

Note: "+" and "-" signs represent the polarity of the wires that make up each wire pair.

Console Port Pin Definition

To connect the console port to an external management device, you need an RJ-45 to DB-9 cable, which is also supplied in the package. Below is the console port pin assignment information.

PC (male) pin assignment	RS-232 with DB9 (female) pin assignment (RJ45-DB9 cable)	RJ45 pin assignment
PIN#2 Rx/D	PIN#2 Rx/D	PIN#2 Rx/D
PIN#3 Tx/D	PIN#3 Tx/D	PIN#3 Tx/D
PIN#5 GND	PIN#5 GND	PIN#5 GND


Wiring

Power inputs

The switch supports dual redundant power supplies, Power Supply1 (PWR1) and Power Supply 2 (PWR2). The connections for PWR1, PWR2 and the RELAY are located on the terminal block.

STEP 1: Insert the negative/positive wires into the V-/V+ terminals, respectively.

STEP 2: To keep the DC wires from pulling loose, use a small flat-blade screwdriver to tighten the wire-clamp screws on the front of the terminal block connector.



Relay contact

The two sets of relay contacts of the 6-pin terminal block connector are used to detect user-configured events. The two wires attached to the fault contacts form an open circuit when a user-configured when an event is triggered. If a user-configured event does not occur, the fault circuit remains closed.

Grounding

Grounding and wire routing help limit the effects of noise due to electromagnetic interference (EMI). Run the ground connection from the ground screws to the grounding surface prior to connecting devices.


Configurations

After installing the switch, the green power LED should turn on. Please refer to the following tablet for LED indication.

LED	Color	Status	Description	LED	Color	Status	Description
PWR	Green	On	DC power on	100/1G/2.5G Base Tx ports			
PWR1	Green	On	DC power module 1 activated	LINK/ACT	Green	On	Port Link/Act.
PWR2	Green	On	DC power module 2 activated			Blinking	Data transmitted.
R.M	Green	On	Ring Master	Speed	Green	On	Link speed is 1 or 2.5Gbps
Ring	Green	On	Ring Slave			On	Link speed is 100Mbps
		Blinking	Ring structure is broken (i.e. part of the ring is disconnected)	PoE	Green	On	Power supplied over Ethernet
Fault	Amber	On	Faulty relay (power failure or port disconnected)	1/10GBase-X SFP+ Ports			
10/100/1000Base-T(X) Gigabit PoE Ethernet ports				LINK/ACT	Green	On	Port Link/Act.
LINK/ACT	Green	On	Port Link/Act.			Blinking	Data transmitted.
		Blinking	Data transmitted.	Speed	Green	On	Link speed is 10Gbps
Speed	Green	On	Link speed is 1Gbps			Off	Link speed is 1Gbps
		Amber	On	Link speed is 100Mbps			
	off	On	Link speed is 10Mbps				
PoE	Green	On	Power supplied over Ethernet				

Follow the steps to set up the switch:

1. Launch the Internet Explorer and type in IP address of the switch. The default static IP address is **192.168.10.1** and default subnet mask is **255.255.255.0**



2. Log in with default user name and password (both are **admin**). After logging in, you should see the following screen. For more information on configurations, please refer to the user manual. For information on operating the switch using ORing's Open-Vision management utility, please go to ORing website.



Resetting

To reboot the switch, press the **Reset** button for 2-3 seconds.

To restore the switch configurations back to the factory defaults, press the **Reset** button for 5 seconds.

ORing

Copyright© 2025 ORing
All rights reserved.

ORing Industrial Networking Corp.

TEL: +886-2-2218-1066 Website: www.oringnet.com
FAX: +886-2-2218-1014 E-mail: support@oringnet.com